

DPCCH-Pilot

Table: Pilot Symbol Pattern

	Npilot = 2	Npilot = 4		Npilot = 8				Npilot = 16							
Symbol #	0	0	1	0	1	2	3	0	1	2	3	4	5	6	7
Slot #0	11	11	11	11	11	11	10	11	11	11	10	11	11	11	10
1	00	11	00	11	00	11	10	11	00	11	10	11	11	11	00
2	01	11	01	11	01	11	01	11	01	11	01	11	10	11	00
3	00	11	00	11	00	11	00	11	00	11	00	11	01	11	10
4	10	11	10	11	10	11	01	11	10	11	01	11	11	11	11
5	11	11	11	11	11	11	10	11	11	11	10	11	01	11	01
6	11	11	11	11	11	11	00	11	11	11	00	11	10	11	11
7	10	11	10	11	10	11	00	11	10	11	00	11	10	11	00
8	01	11	01	11	01	11	10	11	01	11	10	11	00	11	11
9	11	11	11	11	11	11	11	11	11	11	11	11	00	11	11
10	01	11	01	11	01	11	01	11	01	11	01	11	11	11	10
11	10	11	10	11	10	11	11	11	10	11	11	11	00	11	10
12	10	11	10	11	10	11	00	11	10	11	00	11	01	11	01
13	00	11	00	11	00	11	11	11	00	11	11	11	00	11	00
14	00	11	00	11	00	11	11	11	00	11	11	11	10	11	01

Table: Pilot pattern of the DPCH channel for the diversity antenna using STTD

	Npilot = 2	Npilot = 4		Npilot = 8				Npilot = 16							
Symbol #	0	0	1	0	1	2	3	0	1	2	3	4	5	6	7
Slot #0	01	01	10	11	00	00	10	11	00	00	10	11	00	00	10
1	10	10	10	11	00	00	01	11	00	00	01	11	10	00	10
2	11	11	10	11	11	00	00	11	11	00	00	11	10	00	11
3	10	10	10	11	10	00	01	11	10	00	01	11	00	00	00
4	00	00	10	11	11	00	11	11	11	00	11	11	01	00	10
5	01	01	10	11	00	00	10	11	00	00	10	11	11	00	00
6	01	01	10	11	10	00	10	11	10	00	10	11	01	00	11
7	00	00	10	11	10	00	11	11	10	00	11	11	10	00	11
8	11	11	10	11	00	00	00	11	00	00	00	11	01	00	01
9	01	01	10	11	01	00	10	11	01	00	10	11	01	00	01
10	11	11	10	11	11	00	00	11	11	00	00	11	00	00	10
11	00	00	10	11	01	00	11	11	01	00	11	11	00	00	01
12	00	00	10	11	10	00	11	11	10	00	11	11	11	00	00
13	10	10	10	11	01	00	01	11	01	00	01	11	10	00	01
14	10	10	10	11	01	00	01	11	01	00	01	11	11	00	11